



- indicator light for monitoring the demand switch function
 - simple installation by plugging into conventional earthed sockets in the monitored circuit
 - flat design
 - The indicator light KO-L-NA is an indicator light for monitoring the function in a monitored circuit by the mains decoupler series NA. It can be installed by simply plugging it into any socket.
 - The KO-L-NA indicator light shows the respective switching status of the mains decoupler by lighting up orange/red when the mains voltage 230 VAC (alternating current) is switched on during the operation of consumers.
- The indicator light goes out when the 200 VDC (test DC voltage) is applied to the circuit, the mains decoupler is disconnected and all consumers are switched off.

Order-No.: 721039
Short-Desc.: KO-L-NA

Accessories demand switch

Control lamp KO-L-NA

Technical data

length:	42 mm
width:	35 mm
height:	17 mm
protrusion: (in earthed socket)	ca. 7,0 mm
colour:	white
light colour:	orange/red
rated voltage:	230 VAC
performance:	< 0,5 W
protection class:	protective insulation (protection class II)
other features:	▽- suitable for direct fastening on normal flammable surfaces
function:	convenient status display for checking the NA demand switches Series. not for field disconnectors
mains voltage 230 VAC: (consumer switched on)	control lamp = ON
test DC voltage 200 VDC (enabled state, load switched off)	control lamp = OFF

Scope of application

extension or replacement indicator lamp for the field disconnectors of the NA series:

NA 16 Standard

Scope of delivery

control lamp KO-L-NA